



# ENERGY GENERATION

## E4000 230V 50HZ

### ENERGY AT FAIR PRICE



Simple professional generator. Pramac has designed this generator to ensure a high performance level at attractive price. Powerful and strong generator; easy to maintain, it will be soon essential to all your activities.

#### Main Features

Frequency	Hz	50
Voltage	V	230
Power factor	cos $\phi$	0.9
Phase and connection		1

#### Power Rating

Standby power LTP	kVA	3.4
Standby power LTP	kW	3.1
Continuous power COP	kVA	2.9
Continuous power COP	kW	2.6

#### Ratings definition (According to standard ISO8528 1:2005)

**COP** - Continuous Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.

**LTP** - Limited-Time running Power: It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

### Engine specifications

Engine manufacturer		Honda
Model		GX200
Engine cooling system		Air
Displacement	cm <sup>3</sup>	196
Aspiration		Natural
Operating Speed-Nominal	rpm	3000
Speed governor		Mechanical
Fuel		Petrol
Oil capacity	l	0.6
Starting system		Recoil



### Alternator Specifications

Type		Brushless
Class		H
IP protection		23
Poles		2
Frequency	Hz	50
Voltage tolerance	% +5; -10 (cosφ1)	
Voltage regulation system		Capacitor

### Dimensional data

Length	(L) mm	640
Width	(W) mm	458
Height	(H) mm	400
Dry weight	Kg	38
Fuel tank capacity	l	3.1

### Autonomy

Fuel consumption @ 75% PRP	l/h	1.18
Fuel consumption @ 100% PRP	l/h	1.57
Running time @ 75% PRP	h	2.63
Running time @ 100% PRP	h	1.97

### Noise level

Guaranteed noise level (LWA)	dB(A)	96
Noise pressure level @ 7 mt	dB(A)	68

## GENSET CONTROL

### COMMANDS:

- Selector switch: OFF - ON
- Starting systems: Recoil
- Fuel Cock

### PROTECTIONS STANDARD:

- Thermal protection
- Oil Guard

### SOCKET TYPE

SCHUKO 230V 16A IP54

2

## SUPPLEMENTS CONTROL (Available when ordered)

### ASCOFDIFF

Extra Protection with:

- differential protection 30mA
- circuit breaker
- hourmeter



## ACCESSORIES

### TRANSPORTATION KIT

- With fix handles
- With folding handles

